



**Product Description:** Remote power driver, 600W, DMX control, up to 32 channels, constant current, 32 x 48V outputs, 1U 19-in rack

**Input Characteristics:**

Nominal 120 -230V (UL), 6.3A at 120V/60Hz or 5A at 230V/50Hz maximum current, input frequency of 50-60Hz, power factor >0.90, THD at full load is <20%, 91.8% efficient at full load

**Output Characteristics**

Maximum LED output power is 600W, 32 LED outputs, 200-1050mA programmable current range in 50mA steps via display, LED output range is 2-48V

**Control Characteristics**

Up to 32 DMX channels, .01%-100% dimming, three dimming curves: logarithmic (default), linear or square, connectors for each channel provided by Brightline

**Weights and Dimensions**

19.0- x 12.8- x 1.75-in (482.6- x 325.0- x 44.5-mm)  
13.9-lb (6.3kg)  
1U - 19-in (482.6-mm) rack



**Certifications & Warranty**

- CE Directives 2004/108/EC, 2006/95/EC, EN 60929 Annex E
- UL Listed
- 3 year limited warranty

**Part Number Configurations:**

- CTRL-RPD-LV-6060-FLXT for Flex-T*
- CTRL-RPD-LV-6060-LST6 for Stealth-T*
- CTRL-RPD-LV-6060-BL16 for BL.16*
- CTRL-RPD-LV-6060-LVCI for LVCI*
- CTRL-RPD-LV-6060-LMT2 for LED Mirco-T 2-ft*
- CTRL-RPD-LV-6060-LMT4 for LED Micro-T 4-ft*
- CTRL-RPD-LV-6060-LVP2 for LED VideoPlus 2-ft*
- CTRL-RPD-LV-6060-LVP4 for LED VideoPlus 4-ft*

580 Mayer Street - Building # 7 - Bridgeville, PA 15017 USA

Phone: 1.412.206.0106

[www.brightlines.com](http://www.brightlines.com)



© 2019 Brightline LP All Rights Reserved

*Specifications are subject to change without notice.*